

Designer's™ Data Sheet


Medium Power Surface Mount Products

Complementary TMOS

Field Effect Transistors

Micro8™ devices are an advanced series of power MOSFETs which utilize Motorola's High Cell Density HDTMOS process to achieve lowest possible on-resistance per silicon area. They are capable of withstanding high energy in the avalanche and commutation modes and the drain-to-source diode has a very low reverse recovery time. Micro8™ devices are designed for use in low voltage, high speed switching applications where power efficiency is important. Typical applications are dc-dc converters, and power management in portable and battery powered products such as computers, printers, cellular and cordless phones. They can also be used for low voltage motor controls in mass storage products such as disk drives and tape drives. The avalanche energy is specified to eliminate the guesswork in designs where inductive loads are switched and offer additional safety margin against unexpected voltage transients.


- Miniature Micro8 Surface Mount Package — Saves Board Space
- Extremely Low Profile (<1.1mm) for thin applications such as PCMCIA cards
- Ultra Low R_{DS(on)} Provides Higher Efficiency and Extends Battery Life
- Logic Level Gate Drive — Can Be Driven by Logic ICs
- Diode Is Characterized for Use In Bridge Circuits
- Diode Exhibits High Speed, With Soft Recovery
- I_{DSS} Specified at Elevated Temperature
- Avalanche Energy Specified
- Mounting Information for Micro8 Package Provided



MTDF1C02HD
Motorola Preferred Device

**COMPLEMENTARY
DUAL TMOS POWER FET**
20 VOLTS
R_{DS(on)} = 0.120 OHM
1.7 AMPERES
(N-CHANNEL)
R_{DS(on)} = 0.175 OHM
1.6 AMPERES
(P-CHANNEL)

CASE 846A-02, Style 2
Micro8



MAXIMUM RATINGS (T_J = 25°C unless otherwise noted)
Negative sign for P-Channel devices omitted for clarity

Rating		Symbol	Max	Unit
Drain-to-Source Voltage	N-Channel	V _{DSS}	20	V
	P-Channel		20	
Drain-to-Gate Voltage (R _{GS} = 1.0 MΩ)	N-Channel	V _{DGR}	20	V
	P-Channel		20	
Gate-to-Source Voltage — Continuous	N-Channel	V _{GS}	±8.0	V
	P-Channel		±8.0	
Operating and Storage Temperature Range		T _J and T _{stg}	-55 to 150	°C

DEVICE MARKING

CA

ORDERING INFORMATION

Device	Reel Size	Tape Width	Quantity
MTDF1C02HD	13"	12 mm embossed tape	4000 units

Designer's Data for "Worst Case" Conditions — The Designer's Data Sheet permits the design of most circuits entirely from the information presented. SOA Limit curves — representing boundaries on device characteristics — are given to facilitate "worst case" design.

HDTMOS is a trademark of Motorola, Inc. TMOS is a registered trademark of Motorola, Inc. Micro8 is a registered trademark of International Rectifier.

Preferred devices are Motorola recommended choices for future use and best overall value.



MTDF1C02HD

MAXIMUM RATINGS (T_J = 25°C unless otherwise noted)

Rating		Polarity	Symbol	Typical	Max	Unit
Drain-to-Source Voltage		N & P-Ch	V _{DSS}	—	20	V
Drain-to-Gate Voltage (R _{GS} = 1.0 MΩ)		N & P-Ch	V _{DGR}	—	20	V
Gate-to-Source Voltage — Continuous		N & P-Ch	V _{GS}	—	± 8.0	V
1 inch SQ. FR-4 or G-10 PCB Figure A below 1 die operating Steady State	Thermal Resistance — Junction to Ambient	N-Channel	R _{THJA}	80	100	°C/W
	Total Power Dissipation @ T _A = 25°C		P _D	—	1.25	Watts
	Linear Derating Factor		—	—	10	mW/°C
	Drain Current — Continuous @ T _A = 25°C		I _D	—	2.8	A
	Continuous @ T _A = 70°C		I _D	—	2.3	A
Pulsed Drain Current (1)	I _{DM}	—	23	A		
Minimum FR-4 or G-10 PCB Figure B below 1 die operating Steady State	Thermal Resistance — Junction to Ambient	N-Channel	R _{THJA}	160	200	°C/W
	Total Power Dissipation @ T _A = 25°C		P _D	—	0.63	Watts
	Linear Derating Factor		—	—	5.0	mW/°C
	Drain Current — Continuous @ T _A = 25°C		I _D	—	1.7	A
	Continuous @ T _A = 70°C		I _D	—	1.6	A
Pulsed Drain Current (1)	I _{DM}	—	16	A		
1 inch SQ. FR-4 or G-10 PCB Figure A below 1 die operating Steady State	Thermal Resistance — Junction to Ambient	P-Channel	R _{THJA}	80	100	°C/W
	Total Power Dissipation @ T _A = 25°C		P _D	—	1.25	Watts
	Linear Derating Factor		—	—	10	mW/°C
	Drain Current — Continuous @ T _A = 25°C		I _D	—	2.3	A
	Continuous @ T _A = 70°C		I _D	—	1.9	A
Pulsed Drain Current (1)	I _{DM}	—	19	A		
Minimum FR-4 or G-10 PCB Figure B below 1 die operating Steady State	Thermal Resistance — Junction to Ambient	P-Channel	R _{THJA}	160	200	°C/W
	Total Power Dissipation @ T _A = 25°C		P _D	—	0.63	Watts
	Linear Derating Factor		—	—	5.0	mW/°C
	Drain Current — Continuous @ T _A = 25°C		I _D	—	1.6	A
	Continuous @ T _A = 70°C		I _D	—	1.3	A
Pulsed Drain Current (1)	I _{DM}	—	13	A		
Minimum FR-4 or G-10 PCB Figure B below 2 die operating Steady State	Thermal Resistance — Junction to Ambient	N & P-Ch	R _{THJA}	240	300	°C/W
	Total Power Dissipation @ T _A = 25°C		P _D	—	0.42	Watts
	Linear Derating Factor		—	—	3.33	mW/°C
	Drain Current — Continuous @ T _A = 25°C		I _D	—	1.3	A
	Continuous @ T _A = 70°C		I _D	—	1.1	A
Pulsed Drain Current (1)	I _{DM}	—	11	A		
Operating and Storage Temperature Range			T _J , T _{stg}	—	- 55 to 150	°C

(1) Repetitive rating; pulse width limited by maximum junction temperature.




Figure A. 1.0 Inch Square FR-4 or G-10 PCB




Figure B. Minimum FR-4 or G-10 PCB

ELECTRICAL CHARACTERISTICS ($T_A = 25^\circ\text{C}$ unless otherwise noted) (1)

Characteristic	Symbol	Polarity	Min	Typ	Max	Unit
OFF CHARACTERISTICS						
Drain–Source Breakdown Voltage ($C_{pk} \geq 2.0$) ($V_{GS} = 0 \text{ Vdc}$, $I_D = 250 \mu\text{Adc}$)	$V_{(BR)DSS}$	(N) (P)	20 20	— —	— —	Vdc
Breakdown Temperature Coefficient (Positive)		(N) (P)	— —	5.0 14	— —	
Zero Gate Voltage Drain Current ($V_{GS} = 0 \text{ Vdc}$, $V_{DS} = 16 \text{ Vdc}$) ($V_{GS} = 0 \text{ Vdc}$, $V_{DS} = 20 \text{ Vdc}$)	I_{DSS}	(N) (P)	— —	— —	1.0 1.0	μAdc
Gate–Body Leakage Current ($V_{GS} = \pm 8.0 \text{ Vdc}$, $V_{DS} = 0$)	I_{GSS}	—	—	—	100	nAdc

ON CHARACTERISTICS(2)

Gate Threshold Voltage ($C_{pk} \geq 2.0$) ($V_{DS} = V_{GS}$, $I_D = 250 \mu\text{Adc}$)	$V_{GS(th)}$	(N) (P)	0.7 0.7	0.90 0.95	1.1 1.4	Vdc
Threshold Temperature Coefficient (Negative)		(N) (P)	— —	2.5 2.2	— —	
Drain–to–Source On–Resistance ($V_{GS} = 4.5 \text{ Vdc}$, $I_D = 1.7 \text{ Adc}$) ($V_{GS} = 4.5 \text{ Vdc}$, $I_D = 1.6 \text{ Adc}$)	$R_{DS(on)}$	(N) (P)	— —	0.100 0.146	0.120 0.175	Ohm
Drain–to–Source On–Resistance ($C_{pk} \geq 2.0$) ($V_{GS} = 2.7 \text{ Vdc}$, $I_D = 0.85 \text{ Adc}$) ($V_{GS} = 2.7 \text{ Vdc}$, $I_D = 0.8 \text{ Adc}$)	$R_{DS(on)}$	(N) (P)	— —	0.133 0.220	0.16 0.28	Ohm
Forward Transconductance (1) ($V_{DS} = 10 \text{ Adc}$, $I_D = 0.85 \text{ Adc}$) ($V_{DS} = 10 \text{ Adc}$, $I_D = 0.6 \text{ Adc}$)	g_{FS}	(N) (P)	2.0 1.3	— —	— —	mhos

DYNAMIC CHARACTERISTICS

Input Capacitance	$(V_{DS} = 15 \text{ Vdc}$, $V_{GS} = 0 \text{ Vdc}$, $f = 1.0 \text{ MHz}$)	C_{iss}	(N) (P)	— —	145 225	— —	pF
Output Capacitance		C_{oss}	(N) (P)	— —	90 150	— —	
Transfer Capacitance		C_{rss}	(N) (P)	— —	38 60	— —	

SWITCHING CHARACTERISTICS (3)

Turn–On Delay Time	$(V_{DD} = 10 \text{ Vdc}$, $I_D = 1.7 \text{ Adc}$, $V_{GS} = 4.5 \text{ Vdc}$, $R_G = 6.0 \Omega$) (1)	$t_{d(on)}$	(N) (P)	— —	8.0 15	— —	ns
Rise Time		t_r	(N) (P)	— —	27 27	— —	
Turn–Off Delay Time		$t_{d(off)}$	(N) (P)	— —	23 60	— —	
Fall Time		t_f	(N) (P)	— —	34 72	— —	
Turn–On Delay Time	$(V_{DS} = 10 \text{ Vdc}$, $I_D = 0.85 \text{ Adc}$, $V_{GS} = 2.7 \text{ Vdc}$, $R_G = 6.0 \Omega$) (1)	$t_{d(on)}$	(N) (P)	— —	16 20	— —	ns
Rise Time		t_r	(N) (P)	— —	79 94	— —	
Turn–Off Delay Time		$t_{d(off)}$	(N) (P)	— —	24 49	— —	
Fall Time		t_f	(N) (P)	— —	31 76	— —	
Total Gate Charge	$(V_{DS} = 16 \text{ Vdc}$, $I_D = 1.7 \text{ Adc}$, $V_{GS} = 4.5 \text{ Vdc}$) (1)	Q_T	(N) (P)	— —	3.9 5.3	5.5 7.5	nC
Gate–Source Charge		Q_1	(N) (P)	— —	0.4 0.7	— —	
Gate–Drain Charge		Q_2	(N) (P)	— —	1.7 2.6	— —	
	$(V_{DS} = 16 \text{ Vdc}$, $I_D = 1.2 \text{ Adc}$, $V_{GS} = 4.5 \text{ Vdc}$) (1)	Q_3	(N) (P)	— —	1.5 1.9	— —	

(1) Negative signs for P–Channel device omitted for clarity.

(2) Pulse Test: Pulse Width $\leq 300 \mu\text{s}$, Duty Cycle $\leq 2\%$.

(3) Switching characteristics are independent of operating junction temperature.

(continued)

MTDF1C02HD

ELECTRICAL CHARACTERISTICS — continued ($T_A = 25^\circ\text{C}$ unless otherwise noted) (1)

Characteristic	Symbol	Polarity	Min	Typ	Max	Unit
SOURCE-DRAIN DIODE CHARACTERISTICS ($T_C = 25^\circ\text{C}$)						
Forward Voltage (2)	V_{SD}	(N)	—	0.84	1.0	Vdc
		(P)	—	0.89	1.1	
Reverse Recovery Time	t_{rr}	(N)	—	29	—	ns
		(P)	—	86	—	
			(N)	—	14	
		(P)	—	27	—	
		(N)	—	15	—	
		(P)	—	59	—	
Reverse Recovery Stored Charge	Q_{RR}	(N)	—	0.018	—	μC
		(P)	—	0.115	—	

(1) Negative signs for P-Channel device omitted for clarity.

(2) Pulse Test: Pulse Width $\leq 300 \mu\text{s}$, Duty Cycle $\leq 2\%$.

TYPICAL ELECTRICAL CHARACTERISTICS




Figure 1. On-Region Characteristics




Figure 1. On-Region Characteristics




Figure 2. Transfer Characteristics




Figure 2. Transfer Characteristics

TYPICAL ELECTRICAL CHARACTERISTICS

N-Channel




Figure 3. On-Resistance versus Gate-To-Source Voltage

P-Channel




Figure 3. On-Resistance versus Gate-To-Source Voltage




Figure 4. On-Resistance versus Drain Current and Gate Voltage




Figure 4. On-Resistance versus Drain Current and Gate Voltage




Figure 5. On-Resistance Variation with Temperature




Figure 5. On-Resistance Variation with Temperature

TYPICAL ELECTRICAL CHARACTERISTICS




Figure 6. Drain-To-Source Leakage Current versus Voltage




Figure 6. Drain-To-Source Leakage Current versus Voltage

POWER MOSFET SWITCHING

Switching behavior is most easily modeled and predicted by recognizing that the power MOSFET is charge controlled. The lengths of various switching intervals (Δt) are determined by how fast the FET input capacitance can be charged by current from the generator.

The published capacitance data is difficult to use for calculating rise and fall because drain-gate capacitance varies greatly with applied voltage. Accordingly, gate charge data is used. In most cases, a satisfactory estimate of average input current ($I_{G(AV)}$) can be made from a rudimentary analysis of the drive circuit so that

$$t = Q/I_{G(AV)}$$

During the rise and fall time interval when switching a resistive load, V_{GS} remains virtually constant at a level known as the plateau voltage, V_{GSP} . Therefore, rise and fall times may be approximated by the following:

$$t_r = Q_2 \times R_G / (V_{GG} - V_{GSP})$$

$$t_f = Q_2 \times R_G / V_{GSP}$$

where

V_{GG} = the gate drive voltage, which varies from zero to V_{GG}

R_G = the gate drive resistance

and Q_2 and V_{GSP} are read from the gate charge curve.

During the turn-on and turn-off delay times, gate current is not constant. The simplest calculation uses appropriate values from the capacitance curves in a standard equation for voltage change in an RC network. The equations are:

$$t_{d(on)} = R_G C_{iss} \ln [V_{GG}/(V_{GG} - V_{GSP})]$$

$$t_{d(off)} = R_G C_{iss} \ln (V_{GG}/V_{GSP})$$

The capacitance (C_{iss}) is read from the capacitance curve at a voltage corresponding to the off-state condition when calculating $t_{d(on)}$ and is read at a voltage corresponding to the on-state when calculating $t_{d(off)}$.

At high switching speeds, parasitic circuit elements complicate the analysis. The inductance of the MOSFET source lead, inside the package and in the circuit wiring which is common to both the drain and gate current paths, produces a voltage at the source which reduces the gate drive current. The voltage is determined by $L di/dt$, but since di/dt is a function of drain current, the mathematical solution is complex. The MOSFET output capacitance also complicates the mathematics. And finally, MOSFETs have finite internal gate resistance which effectively adds to the resistance of the driving source, but the internal resistance is difficult to measure and, consequently, is not specified.

The resistive switching time variation versus gate resistance (Figure 9) shows how typical switching performance is affected by the parasitic circuit elements. If the parasitics were not present, the slope of the curves would maintain a value of unity regardless of the switching speed. The circuit used to obtain the data is constructed to minimize common inductance in the drain and gate circuit loops and is believed readily achievable with board mounted components. Most power electronic loads are inductive; the data in the figure is taken with a resistive load, which approximates an optimally snubbed inductive load. Power MOSFETs may be safely operated into an inductive load; however, snubbing reduces switching losses.

N-Channel




Figure 7. Capacitance Variation

P-Channel




Figure 7. Capacitance Variation




Figure 8. Gate-To-Source and Drain-To-Source Voltage versus Total Charge




Figure 8. Gate-To-Source and Drain-To-Source Voltage versus Total Charge




Figure 9. Resistive Switching Time Variation versus Gate Resistance




Figure 9. Resistive Switching Time Variation versus Gate Resistance

DRAIN-TO-SOURCE DIODE CHARACTERISTICS

The switching characteristics of a MOSFET body diode are very important in systems using it as a freewheeling or commutating diode. Of particular interest are the reverse recovery characteristics which play a major role in determining switching losses, radiated noise, EMI and RFI.

System switching losses are largely due to the nature of the body diode itself. The body diode is a minority carrier device, therefore it has a finite reverse recovery time, t_{rr} , due to the storage of minority carrier charge, Q_{RR} , as shown in the typical reverse recovery wave form of Figure 14. It is this stored charge that, when cleared from the diode, passes through a potential and defines an energy loss. Obviously, repeatedly forcing the diode through reverse recovery further increases switching losses. Therefore, one would like a diode with short t_{rr} and low Q_{RR} specifications to minimize these losses.

The abruptness of diode reverse recovery effects the amount of radiated noise, voltage spikes, and current ringing. The mechanisms at work are finite irremovable circuit parasitic inductances and capacitances acted upon by high

di/dt s. The diode's negative di/dt during t_a is directly controlled by the device clearing the stored charge. However, the positive di/dt during t_b is an uncontrollable diode characteristic and is usually the culprit that induces current ringing. Therefore, when comparing diodes, the ratio of t_b/t_a serves as a good indicator of recovery abruptness and thus gives a comparative estimate of probable noise generated. A ratio of 1 is considered ideal and values less than 0.5 are considered snappy.

Compared to Motorola standard cell density low voltage MOSFETs, high cell density MOSFET diodes are faster (shorter t_{rr}), have less stored charge and a softer reverse recovery characteristic. The softness advantage of the high cell density diode means they can be forced through reverse recovery at a higher di/dt than a standard cell MOSFET diode without increasing the current ringing or the noise generated. In addition, power dissipation incurred from switching the diode will be less due to the shorter recovery time and lower switching losses.

N-Channel




Figure 10. Diode Forward Voltage versus Current

P-Channel




Figure 10. Diode Forward Voltage versus Current




Figure 11. Reverse Recovery Time (t_{rr})

SAFE OPERATING AREA

The Forward Biased Safe Operating Area curves define the maximum simultaneous drain-to-source voltage and drain current that a transistor can handle safely when it is forward biased. Curves are based upon maximum peak junction temperature and a case temperature (T_C) of 25°C. Peak repetitive pulsed power limits are determined by using the thermal response data in conjunction with the procedures discussed in AN569, "Transient Thermal Resistance – General Data and Its Use."

Switching between the off-state and the on-state may traverse any load line provided neither rated peak current (I_{DM}) nor rated voltage (V_{DSS}) is exceeded, and that the transition time (t_r , t_f) does not exceed 10 μ s. In addition the total power

averaged over a complete switching cycle must not exceed $(T_{J(MAX)} - T_C)/(R_{\theta JC})$.

A power MOSFET designated E-FET can be safely used in switching circuits with unclamped inductive loads. For reliable operation, the stored energy from circuit inductance dissipated in the transistor while in avalanche must be less than the rated limit and must be adjusted for operating conditions differing from those specified. Although industry practice is to rate in terms of energy, avalanche energy capability is not a constant. The energy rating decreases non-linearly with an increase of peak current in avalanche and peak junction temperature.




Figure 12. Maximum Rated Forward Biased Safe Operating Area




Figure 12. Maximum Rated Forward Biased Safe Operating Area

TYPICAL ELECTRICAL CHARACTERISTICS




Figure 13. Thermal Response





Figure 14. Diode Reverse Recovery Waveform

INFORMATION FOR USING THE SO-8 SURFACE MOUNT PACKAGE

MINIMUM RECOMMENDED FOOTPRINT FOR SURFACE MOUNTED APPLICATIONS

Surface mount board layout is a critical portion of the total design. The footprint for the semiconductor packages must be the correct size to ensure proper solder connection interface

between the board and the package. With the correct pad geometry, the packages will self-align when subjected to a solder reflow process.



SO-8 POWER DISSIPATION

The power dissipation of the SO-8 is a function of the input pad size. This can vary from the minimum pad size for soldering to the pad size given for maximum power dissipation. Power dissipation for a surface mount device is determined by $T_{J(max)}$, the maximum rated junction temperature of the die, $R_{\theta JA}$, the thermal resistance from the device junction to ambient; and the operating temperature, T_A . Using the values provided on the data sheet for the SO-8 package, P_D can be calculated as follows:

$$P_D = \frac{T_{J(max)} - T_A}{R_{\theta JA}}$$

The values for the equation are found in the maximum ratings table on the data sheet. Substituting these values into

the equation for an ambient temperature T_A of 25°C, one can calculate the power dissipation of the device which in this case is 0.63 Watts.

$$P_D = \frac{150^\circ\text{C} - 25^\circ\text{C}}{200^\circ\text{C/W}} = 0.63 \text{ Watts}$$

The 200°C/W for the SO-8 package assumes the recommended footprint on a glass epoxy printed circuit board to achieve a power dissipation of 0.63 Watts using the footprint shown. Another alternative would be to use a ceramic substrate or an aluminum core board such as Thermal Clad™. Using board material such as Thermal Clad, the power dissipation can be doubled using the same footprint.

SOLDERING PRECAUTIONS

The melting temperature of solder is higher than the rated temperature of the device. When the entire device is heated to a high temperature, failure to complete soldering within a short time could result in device failure. Therefore, the following items should always be observed in order to minimize the thermal stress to which the devices are subjected.

- Always preheat the device.
- The delta temperature between the preheat and soldering should be 100°C or less.*
- When preheating and soldering, the temperature of the leads and the case must not exceed the maximum temperature ratings as shown on the data sheet. When using infrared heating with the reflow soldering method, the difference shall be a maximum of 10°C.

- The soldering temperature and time shall not exceed 260°C for more than 10 seconds.
- When shifting from preheating to soldering, the maximum temperature gradient shall be 5°C or less.
- After soldering has been completed, the device should be allowed to cool naturally for at least three minutes. Gradual cooling should be used as the use of forced cooling will increase the temperature gradient and result in latent failure due to mechanical stress.
- Mechanical stress or shock should not be applied during cooling.

* Soldering a device without preheating can cause excessive thermal shock and stress which can result in damage to the device.

TYPICAL SOLDER HEATING PROFILE

For any given circuit board, there will be a group of control settings that will give the desired heat pattern. The operator must set temperatures for several heating zones and a figure for belt speed. Taken together, these control settings make up a heating "profile" for that particular circuit board. On machines controlled by a computer, the computer remembers these profiles from one operating session to the next. Figure 15 shows a typical heating profile for use when soldering a surface mount device to a printed circuit board. This profile will vary among soldering systems, but it is a good starting point. Factors that can affect the profile include the type of soldering system in use, density and types of components on the board, type of solder used, and the type of board or substrate material being used. This profile shows temperature versus time. The

line on the graph shows the actual temperature that might be experienced on the surface of a test board at or near a central solder joint. The two profiles are based on a high density and a low density board. The Vitronics SMD310 convection/infrared reflow soldering system was used to generate this profile. The type of solder used was 62/36/2 Tin Lead Silver with a melting point between 177–189°C. When this type of furnace is used for solder reflow work, the circuit boards and solder joints tend to heat first. The components on the board are then heated by conduction. The circuit board, because it has a large surface area, absorbs the thermal energy more efficiently, then distributes this energy to the components. Because of this effect, the main body of a component may be up to 30 degrees cooler than the adjacent solder joints.





Figure 15. Typical Solder Heating Profile

PACKAGE DIMENSIONS



- NOTES:
1. DIMENSIONING AND TOLERANCING PER ANSI Y14.5M, 1982.
 2. CONTROLLING DIMENSION: MILLIMETER.
 3. DIMENSION A DOES NOT INCLUDE MOLD FLASH, PROTRUSIONS OR GATE BURRS. MOLD FLASH, PROTRUSIONS OR GATE BURRS SHALL NOT EXCEED 0.15 (0.006) PER SIDE.
 4. DIMENSION B DOES NOT INCLUDE INTERLEAD FLASH OR PROTRUSION. INTERLEAD FLASH OR PROTRUSION SHALL NOT EXCEED 0.25 (0.010) PER SIDE.

DIM	MILLIMETERS		INCHES	
	MIN	MAX	MIN	MAX
A	2.90	3.10	0.114	0.122
B	2.90	3.10	0.114	0.122
C	—	1.10	—	0.043
D	0.25	0.40	0.010	0.016
G	0.65 BSC		0.026 BSC	
H	0.05	0.15	0.002	0.006
J	0.13	0.23	0.005	0.009
K	4.75	5.05	0.187	0.199
L	0.40	0.70	0.016	0.028

- STYLE 2:
1. SOURCE 1
 2. GATE 1
 3. SOURCE 2
 4. GATE 2
 5. DRAIN 2
 6. DRAIN 2
 7. DRAIN 1
 8. DRAIN 1

CASE 846A-02
ISSUE C
MICRO8

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters which may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part. Motorola and  are registered trademarks of Motorola, Inc. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

Mfax is a trademark of Motorola, Inc.

How to reach us:

USA/EUROPE/Locations Not Listed: Motorola Literature Distribution;
P.O. Box 5405, Denver, Colorado 80217. 303-675-2140 or 1-800-441-2447

JAPAN: Nippon Motorola Ltd.; Tatsumi-SPD-JLDC, 6F Seibu-Butsuryu-Center,
3-14-2 Tatsumi Koto-Ku, Tokyo 135, Japan. 81-3-3521-8315

Mfax™: RMFAX0@email.sps.mot.com – TOUCHTONE 602-244-6609
INTERNET: <http://Design-NET.com>

ASIA/PACIFIC: Motorola Semiconductors H.K. Ltd.; 8B Tai Ping Industrial Park,
51 Ting Kok Road, Tai Po, N.T., Hong Kong. 852-26629298



MOTOROLA

