

To all our customers

Regarding the change of names mentioned in the document, such as Hitachi Electric and Hitachi XX, to Renesas Technology Corp.

The semiconductor operations of Mitsubishi Electric and Hitachi were transferred to Renesas Technology Corporation on April 1st 2003. These operations include microcomputer, logic, analog and discrete devices, and memory chips other than DRAMs (flash memory, SRAMs etc.) Accordingly, although Hitachi, Hitachi, Ltd., Hitachi Semiconductors, and other Hitachi brand names are mentioned in the document, these names have in fact all been changed to Renesas Technology Corp. Thank you for your understanding. Except for our corporate trademark, logo and corporate statement, no changes whatsoever have been made to the contents of the document, and these changes do not constitute any alteration to the contents of the document itself.

Renesas Technology Home Page: <http://www.renesas.com>

Renesas Technology Corp.
Customer Support Dept.
April 1, 2003

Cautions

Keep safety first in your circuit designs!

1. Renesas Technology Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage.

Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corporation product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corporation or a third party.
2. Renesas Technology Corporation assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corporation or an authorized Renesas Technology Corporation product distributor for the latest product information before purchasing a product listed herein.
The information described here may contain technical inaccuracies or typographical errors. Renesas Technology Corporation assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
Please also pay attention to information published by Renesas Technology Corporation by various means, including the Renesas Technology Corporation Semiconductor home page (<http://www.renesas.com>).
4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corporation assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
5. Renesas Technology Corporation semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corporation or an authorized Renesas Technology Corporation product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
6. The prior written approval of Renesas Technology Corporation is necessary to reprint or reproduce in whole or in part these materials.
7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
8. Please contact Renesas Technology Corporation for further details on these materials or the products contained therein.

HTT1129E

Silicon NPN Epitaxial Twin Transistor

RENESAS

ADE-208-1541A (Z)

Rev.1
Jan. 2003


Features

- Include 2 transistors in a small size SMD package: EMFPAK-6 (6 Leads: 1.2 x 0.8 x 0.5 mm)


Q1: Equivalent Buffer transistor	Q2: Equivalent OSC transistor
2SC5849	2SC5872

Outline

EMFPAK-6



Pin Arrangement



- | | |
|-----------------|---------------|
| 1. Collector Q1 | 4. Base Q2 |
| 2. Emitter Q1 | 5. Emitter Q2 |
| 3. Collector Q2 | 6. Base Q1 |


Note: Mark is "Z".

Absolute Maximum Ratings

($T_a = 25\text{ }^\circ\text{C}$)

Item	Symbol	Ratings		Unit
		Q1	Q2	
Collector to base voltage	V_{CBO}	15	15	V
Collector to emitter voltage	V_{CEO}	6	6	V
Emitter to base voltage	V_{EBO}	1.5	0.8	V
Collector current	I_C	80	50	mA
Collector power dissipation	P_C	Total 200*		mW
Junction temperature	T_j	150	150	$^\circ\text{C}$
Storage temperature	T_{stg}	-55 to +150	-50 to +150	$^\circ\text{C}$

*Value on PCB. (FR-4 (13 x 13 x 0.635 mm)).



Q1 Electrical Characteristics

(Ta = 25°C)





Item	Symbol	Min	Typ	Max	Unit	Test Condition
Collector to base breakdown voltage	$V_{(BR)CBO}$	15	—	—	V	$I_C = 10 \mu A, I_E = 0$
Collector cutoff current	I_{CBO}	—	—	0.1	μA	$V_{CB} = 15 V, I_E = 0$
Collector cutoff current	I_{CEO}	—	—	0.1	μA	$V_{CE} = 6 V, R_{BE} = \text{infinite}$
Emitter cutoff current	I_{EBO}	—	—	0.1	μA	$V_{EB} = 1.5 V, I_C = 0$
DC current transfer ratio	h_{FE}	90	120	140	—	$V_{CE} = 1 V, I_C = 5 \text{ mA}$
Reverse transfer capacitance	C_{re}	—	0.50	0.65	pF	$V_{CB} = 1 V, f = 1 \text{ MHz}$ Emitter ground
Gain bandwidth product	f_T	2	4	—	GHz	$V_{CE} = 1 V, I_C = 5 \text{ mA}, f = 1 \text{ GHz}$
Forward transfer coefficient	$ S_{21} ^2$	7	11	—	dB	$V_{CE} = 1 V, I_C = 5 \text{ mA},$ $f = 900 \text{ MHz},$
Noise figure	NF	—	1.7	2.3	dB	$\Gamma_S = \Gamma_L = 50 \Omega$

Q2 Electrical Characteristics


(Ta = 25°C)

Item	Symbol	Min	Typ	Max	Unit	Test Condition
Collector to base breakdown voltage	$V_{(BR)CBO}$	16	—	—	V	$I_C = 10 \mu A, I_E = 0$
Collector cutoff current	I_{CBO}	—	—	0.1	μA	$V_{CB} = 15 V, I_E = 0$
Collector cutoff current	I_{CEO}	—	—	0.1	μA	$V_{CE} = 6 V, R_{BE} = \text{infinite}$
Emitter cutoff current	I_{EBO}	—	—	0.1	μA	$V_{EB} = 0.8 V, I_C = 0$
DC current transfer ratio	h_{FE}	90	120	140	—	$V_{CE} = 1 V, I_C = 5 \text{ mA}$
Reverse transfer capacitance	C_{re}	—	0.25	0.35	pF	$V_{CB} = 1 V, f = 1 \text{ MHz}$ Emitter ground
Gain bandwidth product	f_T	8	10	—	GHz	$V_{CE} = 1 V, I_C = 5 \text{ mA}, f = 1 \text{ GHz}$
Forward transfer coefficient	$ S_{21} ^2$	13	16	—	dB	$V_{CE} = 1 V, I_C = 5 \text{ mA},$ $f = 900 \text{ MHz}$
Noise figure	NF	—	1.0	1.6	dB	$\Gamma_S = \Gamma_L = 50 \Omega$


Q1 Main Characteristics




Gain Bandwidth Product vs. Collector Current







Noise Figure vs. Collector Current




S₂₁ Parameter vs. Collector Current




Q2 Main Characteristics




Gain Bandwidth Product vs. Collector Current



Noise Figure vs. Collector Current




S_{21} Parameter vs. Collector Current



Package Dimensions

As of July, 2002

Unit: mm



Hitachi Code	EMFPAK-6
JEDEC	—
JEITA	—
Mass (reference value)	0.0012 g

Disclaimer

1. Hitachi neither warrants nor grants licenses of any rights of Hitachi's or any third party's patent, copyright, trademark, or other intellectual property rights for information contained in this document. Hitachi bears no responsibility for problems that may arise with third party's rights, including intellectual property rights, in connection with use of the information contained in this document.
2. Products and product specifications may be subject to change without notice. Confirm that you have received the latest product standards or specifications before final design, purchase or use.
3. Hitachi makes every attempt to ensure that its products are of high quality and reliability. However, contact Hitachi's sales office before using the product in an application that demands especially high quality and reliability or where its failure or malfunction may directly threaten human life or cause risk of bodily injury, such as aerospace, aeronautics, nuclear power, combustion control, transportation, traffic, safety equipment or medical equipment for life support.
4. Design your application so that the product is used within the ranges guaranteed by Hitachi particularly for maximum rating, operating supply voltage range, heat radiation characteristics, installation conditions and other characteristics. Hitachi bears no responsibility for failure or damage when used beyond the guaranteed ranges. Even within the guaranteed ranges, consider normally foreseeable failure rates or failure modes in semiconductor devices and employ systemic measures such as fail-safes, so that the equipment incorporating Hitachi product does not cause bodily injury, fire or other consequential damage due to operation of the Hitachi product.
5. This product is not designed to be radiation resistant.
6. No one is permitted to reproduce or duplicate, in any form, the whole or part of this document without written approval from Hitachi.
7. Contact Hitachi's sales office for any questions regarding this document or Hitachi semiconductor products.

Sales Offices

HITACHI

Hitachi, Ltd.

Semiconductor & Integrated Circuits
Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan
Tel: (03) 3270-2111 Fax: (03) 3270-5109

URL <http://www.hitachisemiconductor.com/>

For further information write to:

Hitachi Semiconductor (America) Inc. 179 East Tasman Drive San Jose, CA 95134 Tel: <1> (408) 433-1990 Fax: <1> (408) 433-0223	Hitachi Europe Ltd. Electronic Components Group Whitebrook Park Lower Cookham Road Maidenhead Berkshire SL6 8YA, United Kingdom Tel: <44> (1628) 585000 Fax: <44> (1628) 778322
--	--

Hitachi Europe GmbH Electronic Components Group Dornacher Str 3 D-85622 Feldkirchen Postfach 201, D-85619 Feldkirchen Germany Tel: <49> (89) 9 9180-0 Fax: <49> (89) 9 29 30 00
--

Hitachi Asia Ltd. Hitachi Tower 16 Collyer Quay #20-00 Singapore 049318 Tel: <65>-6538-6533/6538-8577 Fax: <65>-6538-6933/6538-3877 URL: http://semiconductor.hitachi.com.sg
--

Hitachi Asia Ltd. (Taipei Branch Office) 4/F, No. 167, Tun Hwa North Road Hung-Kuo Building Taipei (105), Taiwan Tel: <886>-(2)-2718-3666 Fax: <886>-(2)-2718-8180 Telex: 23222 HAS-TP URL: http://semiconductor.hitachi.com.tw

Hitachi Asia (Hong Kong) Ltd. Group III (Electronic Components) 7/F., North Tower World Finance Centre, Harbour City, Canton Road Tsim Sha Tsui, Kowloon Hong Kong Tel: <852>-2735-9218 Fax: <852>-2730-0281 URL: http://semiconductor.hitachi.com.hk

Copyright © Hitachi, Ltd., 2003. All rights reserved. Printed in Japan.
Colophon 7.0