

MN101E77 Series (Tentative)

8-bit Single-chip Microcontroller

■ Overview

The MN101E series of 8-bit single-chip microcomputers (the memory expansion version of MN101C series) incorporate multiple types of peripheral functions. This chip series is well suited for camera, VCR, MD, TV, CD, LD, printer, telephone, home automation, pager, air conditioner, PPC, remote controller, fax machine, music instrument and other applications.

This LSI brings to embedded microcomputer and applications flexible, optimized hardware configurations and a simple efficient instruction set. MN101EF77G has an internal 128 KB of ROM 2 KB of RAM. Peripheral functions include 6 external interrupts, 13 internal interrupts including NMI, 7 timer counters, 1 type of serial interfaces, A/D converter and 2 types of watchdog timer. The system configuration is suitable for system control microcontroller such as camera, timer selector for VCR, CD player, or MD.

With 4 oscillation systems (high-speed (internal frequency: 16 MHz), high-speed (crystal/ceramic frequency: max. 10 MHz) / low-speed (internal frequency: 5 kHz), low-speed (crystal frequency: 32.768 kHz) contained on the chip, the system clock can be switched to high-speed frequency input (NORMAL mode) or to low-speed frequency input (SLOW mode).

The system clock is generated by dividing the oscillation clock. The best operation clock for the system can be selected by switching its frequency ratio by programming. High speed mode has the standard mode which is based on the clock dividing f_{xtl}/f_{rc} by 2 ($f_{xtl}/2$ or $f_{rc}/2$), and the double speed mode which is based on the clock not dividing f_{xtl} or f_{rc} .

A machine cycle (minimum instruction execution time) in the standard mode is 200 ns when the original oscillation f_{xtl} is 10 MHz. A machine cycle in the double speed mode, in which the CPU operates on the same clock as the external clock, is 100 ns when f_{xtl} is 10 MHz.

■ Product Summary

This datasheet describes the following model.

Model	ROM Size	RAM Size	Classification	Package
MN101EF77G	128 KB	2 KB	Flash EEPROM version	HQFP048-P-0707B

■ Features

- ROM Size:
 - 128 KB (131072 × 8-bit)
- RAM Size:
 - 2 KB (2048 × 8-bit)
- Package:
 - 48-HQFP (7 mm × 7 mm, 0.50 mm pitch) * *: halogen free package
- Machine Cycle:
 - High speed mode 1 (External high speed oscillation) <fs = fxtl / 1>
 - 0.125 μs / 8 MHz (2.0 V to 3.6 V)
 - 0.250 μs / 4 MHz (V_{RSTL} to 3.6 V)
 - High speed mode 2 (Internal high speed oscillation) <fs = frc / 2>
 - 0.125 μs / 8 MHz (V_{RSTL} to 3.6 V)
 - * It is necessary to set Handshake mode
 - Low speed mode 1 (External low speed oscillation) <fs = fxtls / 2>
 - 61.04 μs / 32.768 kHz (V_{RSTL} to 3.6 V)
 - Low speed mode 2 (Internal low speed oscillation) <fs = frcs / 2>
 - 400 μs / 5 kHz (V_{RSTL} to 3.6 V)
- Clock Gear Circuit Embedded:
 - The operation speed of system clock can be changed by switching the dividing ratio of the oscillation clock (fosc,fx) (1, 2, 4, 8, 16, 32, 64, 128 dividing)
 - * fosc : High speed clock switched between Internal and External High speed oscillation
 - fx : Low speed clock switched between Internal and External low speed oscillation
- Oscillation Circuit:
 - External high speed oscillation (fxtl) : (crystal/ ceramic)
 - Internal high speed oscillation (frc) : 16 MHz ± 2 %
 - External low speed oscillation (fxtls) : (crystal)
 - Internal low speed oscillation (frcs) : 5 kHz ± 10 %
- Operation Modes:
 - NORMAL mode (High-speed mode)
 - SLOW mode (Low-speed mode)
 - HALT mode (High-speed / Low-speed mode)
 - STOP mode
 - The operation clock can be switched in each mode.
- ROM Correction:
 - Maximum of 3 parts in a program
- Operation Voltage:
 - V_{RSTL} to 3.6 V (V_{RSTL} : Auto Reset Voltage 1.95 V ± 0.15 V)
- Operating Temperature:
 - 20°C to +60°C

■ Features (continued)**• Interrupt: 24 interrupts**

<External Interrupt> Rising / falling edge can be specified.

IRQ0 – External Interrupt (Edge selectable, Noise filter connectable)

IRQ1 – External Interrupt (Edge selectable, Noise filter connectable)

IRQ2 – External Interrupt (Edge selectable, Both edges selectable)

IRQ3 – External Interrupt (Edge selectable, Both edges selectable)

IRQ4 – External Interrupt (Edge selectable, Both edges selectable)

IRQ6 – External Interrupt (Key scan interrupt)

<Timer Interrupt>

TM0IRQ – Timer 0 interrupt (8-bit timer)

TM1IRQ – Timer 1 interrupt (8-bit timer)

TM2IRQ – Timer 2 interrupt (8-bit timer)

TM3IRQ – Timer 3 interrupt (8-bit timer)

TM6IRQ – Timer 6 interrupt (8-bit timer)

TM7IRQ – Timer 7 interrupt (16-bit timer)

T7OC2IRQ – Timer 7 compare register 2 interrupt (16-bit timer)

TM8IRQ – Timer 8 interrupt (16-bit timer)

T8OC2IRQ – Timer 8 compare register 2 interrupt (16-bit timer)

TBIRQ – Time base timer interrupt

<Serial Interface Interrupt>

SC0RIRQ – Serial 0 UART reception interrupt (UART reception)

SC0TIRQ – Serial 0 UART transmission interrupt (UART transmission, synchronous)

SC1RIRQ – Serial 1 UART reception interrupt (UART reception)

SC1TIRQ – Serial 1 UART transmission interrupt (UART transmission, synchronous)

SC4IRQ – Serial 4 interrupt (Multi master IIC communication, synchronous)

SC4STPCIRQ – Serial 4 interrupt (Multi master IIC stop condition)

<Overrun Interrupt>

NMI – Non-maskable interrupt

<A/D Conversion Interrupt>

ADIRQ – A/D conversion end

• A/D Converter:

10-bit × 9 channels

• Gain-Amp:

2 channels

• Reference Power Supply:

1.7 V ± 0.1 V

• Voice-Amp:

ABclass Amp

Built in speaker disconnection detector circuit

Amplitude gain selectable

* Low pass filter for extracting voice signal from PWM output is not built in

■ Features (continued)

- **Timer Counter:** 10 Timers (All timer counters generate interrupts.)

Timer 0 – 8-bit timer

Square wave output, PWM output, Simple pulse width measurement
 Added pulse (2-bit) system PWM
 Clock source : f_{osc} , $f_{osc}/4$, $f_{osc}/16$, $f_{osc}/32$, $f_{osc}/64$, $f_s/2$, $f_s/4$, f_x , external clock
 Square wave output and PWM output can be output to the large current pin P30(TM00)

Timer 1 – 8-bit timer

Timer 0 and 1 can be connected in cascade
 Clock source : f_{osc} , $f_{osc}/4$, $f_{osc}/16$, $f_{osc}/64$, $f_{osc}/128$, $f_s/2$, $f_s/8$, f_x
 Usable as UART baud rate timer

Timer 2 – 8-bit timer

Square wave output, PWM output, Simple pulse width measurement,
 Added pulse (2-bit) system PWM,
 Clock source : f_{osc} , $f_{osc}/4$, $f_{osc}/16$, $f_{osc}/32$, $f_{osc}/64$, $f_s/2$, $f_s/4$, f_x , external clock
 Square wave output and PWM output can be output to the large current pin P32(TM20).
 Usable as UART baud rate timer

Timer 3 – 8-bit timer

Timer 2 and Timer 3 can be connected in cascade
 Clock source : f_{osc} , $f_{osc}/4$, $f_{osc}/16$, $f_{osc}/64$, $f_{osc}/128$, $f_s/2$, $f_s/8$, f_x

Timer 6 – 8-bit timer

Timer 6 can be combined to Time base timer
 Clock source : f_{osc} , f_s , f_x , time base output ($1/2^7$ or $1/2^{13}$)

Timer 7 – 16-bit timer (Double buffer composition)

Square wave output, PWM output (duty/cycle continuous changeable), Event count,
 Pulse width measurement, Input capture
 PWM output can be output to the large current pin P31 (TM70).
 Clock source : Dividing f_{osc} , f_s , external clock in 1, 2, 4 or 16

Timer 8 – 16-bit timer (Double buffer composition)

Square wave output, PWM output (duty/cycle continuous changeable), Event count,
 Pulse width measurement, Input capture
 PWM output can be output to the large current pin P33 (TM80).
 Clock source: Dividing f_{osc} , f_s , external clock in 1, 2, 4 or 16

Time base timer

Clock source : f_{osc} , f_x
 Interrupt generation cycle : $f_{osc}/2^7$, $f_{osc}/2^8$, $f_{osc}/2^9$, $f_{osc}/2^{10}$, $f_{osc}/2^{12}$, $f_{osc}/2^{13}$, $f_{osc}/2^{14}$, $f_{osc}/2^{15}$,
 $f_x/2^7$, $f_x/2^8$, $f_x/2^9$, $f_x/2^{10}$, $f_x/2^{12}$, $f_x/2^{13}$, $f_x/2^{14}$, $f_x/2^{15}$

Watchdog timer

Error detection cycle: selectable from $f_s/2^{16}$, $f_s/2^{18}$, and $f_s/2^{20}$.

Watchdog timer 2

Error detection cycle: selectable from $f_{rcs}/2^{11}$, $f_{rcs}/2^{12}$, $f_{rcs}/2^{14}$, and $f_{rcs}/2^{16}$.

- **Clock output:**

OSC source oscillation, system clock or internal low-speed clock can be output.

■ Features (continued)

• Serial Interface: 3 channel

<Serial interface 0>

CH0 – 3 channel type synchronous / UART (full duplex)

Transfer clock: $1/2$ of $f_{osc}/2$, $f_{osc}/4$, $f_{osc}/16$, $f_{osc}/64$, $f_s/2$, $f_s/4$, timer1 or 2 output

At UART, timer1 or 2 are used as a baud rate timer

MSB/LSB can be selected as the first bit to be transferred.

Any transfer size from 1 to 8 bits can be selected.

Parity check, parity addition, overrun and framing error detection.

Usable as 2 channel type serial interface.

<Serial interface 1>

CH1 – 3 channel type synchronous / UART (full duplex)

Transfer clock: $1/2$ of $f_{osc}/2$, $f_{osc}/4$, $f_{osc}/16$, $f_{osc}/64$, $f_s/2$, $f_s/4$, timer0 or 1 output

At UART, timer0 or 1 are used as a baud rate timer

MSB/LSB can be selected as the first bit to be transferred.

Any transfer size from 1 to 8 bits can be selected.

Parity check, parity addition, overrun and framing error detection.

Usable as 2 channel type serial interface.

<Serial interface 4>

CH4 – 3 channel type synchronous / Multi master IIC interface

Transfer clock: $1/2$ of $f_{osc}/2$, $f_{osc}/4$, $f_{osc}/16$, $f_{osc}/64$, $f_s/2$, $f_s/4$, timer2 or 3 output

MSB/LSB can be selected as the first bit to be transferred.

Any transfer size from 1 to 8 bits can be selected.

Usable as 2 channel type serial interface.

7-bit or 10-bit slave address is available. (Multi master IIC)

Support general call communication mode. (Multi master IIC)

• Buzzer output:

Output frequency can be selected from

 $f_{osc}/2^{14}$, $f_{osc}/2^{13}$, $f_{osc}/2^{12}$, $f_{osc}/2^{11}$, $f_{osc}/2^{10}$, $f_{osc}/2^9$, $f_x/2^4$, $f_x/2^3$

• LED driver:


7 pins (3 pins are used for Nch open-drain output)

■ Features (continued)

- Port: I/O ports 35 ports (All ports are multi purpose)
 - LED (large current) driver ports 7 ports (switchable with timer output)
 - A/D input pins 9 pins
 - Timer output pin 5 pin
 - Timer I/O pins 2 pins
 - External interrupt pins 5 pins
 - Serial port pins 9 pins
 - Oscillator pins 4 pins
 - Gain-Amp pins 6 pins
 - Reference voltage output pin 1 pin
 - Key interrupt pins 8 pins
 - Buzzer output pin 1 pin
 - Clock output pin 1 pin
- Special pin
 - A/D Reference voltage input pin 1 pin
 - Power Supply pin 2 pins
 - Voice Amp power supply pin 2 pins
 - Voice Amp input pin 1 pin
 - Voice Amp Bias pin 1 pin (for connecting condenser)
 - Speaker Connection pin 2 pins
 - Operation mode setting pin 2 pins
 - Reset input pin 1 pin
 - Condenser connection pin 1 pin

■ Pin Description

- HQFP048-P-0707B



Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products. No license is granted in and to any intellectual property right or other right owned by Panasonic Corporation or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for general applications (such as office equipment, communications equipment, measuring instruments and household appliances), or for specific applications as expressly stated in this book.
Consult our sales staff in advance for information on the following applications:
 - Special applications (such as for airplanes, aerospace, automotive equipment, traffic signaling equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.It is to be understood that our company shall not be held responsible for any damage incurred as a result of or in connection with your using the products described in this book for any special application, unless our company agrees to your using the products in this book for any special application.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of our company.