

**UM66T Simple Melody Generator****Features**

- 64-note ROM memory
- 1.3V to 3.3V operating voltage and low power consumption
- Packaged in inexpensive TO-92 package
- Built-in RC oscillator
- Level-hold mode to play repeatedly
- Dynamic speaker can be driven with external NPN transistor.

**General Description**

The UM66T series is a CMOS LSI designed melody generator IC for use in telephones and toys application. It has an on-chip ROM programmed for musical performance. Produced by CMOS technology, the device results in very low power consumption. And with built-in RC oscillator, a compact melody module can be constructed with only a few additional components.

**Absolute Maximum Ratings**

DC Supply Voltage ..... -0.3V to +5.0V  
 Operating Ambient Temperature ..... -10°C to 60°C  
 Storage Temperature ..... -55°C to 125°C

**Electrical Characteristics**


(V<sub>SS</sub>=0V, V<sub>DD</sub>=1.5V, T<sub>a</sub>=25°C, unless otherwise specified.)

Parameter	Symbol	Min.	Typ.	Max.	Conditions
Operating voltage	V <sub>DD</sub>	1.3V	1.5V	3.3V	
Current Consumption	I <sub>DD</sub>	-	16μA	50μA	Playing with no load
Output Current	I <sub>o/p</sub>	2mA	-	-	
Osc. frequency	F <sub>osc</sub>	63kHz	90kHz	117kHz	

**Song Series List**

Part number	Song name
UM66T-01L	Jingle Bells + Santa Claus Is Coming To Town + We Wish You A Merry Christmas
UM66T-05L	Home Sweet Home
UM66T-09L	Wedding March (Mendelssohn)
UM66T-19L	For Alice
UM66T-32L	Coo Coo Waltz
UM66T-68L	It Is A Small World


### Pin Configuration (Front View)




Pin no.	Symbol	Description
1	O/P	Melody Output
2	VDD	Positive Power Supply
3	Vss	Negative Power Supply

### Typical Application Circuits

LEVEL HOLD MODE FOR SPEAKER



LEVEL HOLD MODE FOR PIEZO BUZZER



Recommended values : C = 1 $\mu$ F , R = 4.7K $\Omega$  , Q = 2SC9013

REV.9-2008 (2 pages)