



4-Bit Programmable

28-Pin DIP 4 -Pole Filters

Description:

The 424 and 428 Series of high-performance, linear active filters represent a breakthrough line of 4- and 8-pole programmable filters. These new filters take advantage of the company's proprietary designs using surface mount technology to duplicate the specifications of the current products in a low profile, compact package that occupies 60% less board space. Available low-pass and high-pass models are factory tuned to one of 10 preset 4-bit binary ranges or one of 7 log-weighted ranges from 10 Hz to 102.4 kHz. Contact factory for custom discrete tuning ranges (maximum span 1000:1).


Features/Benefits:

- Compact 1.8"L x 0.8"W x 0.3"H min. (28 pin DIP footprint) minimizes board space requirements.
- Low harmonic distortion and wide signal-to-noise ratio to 16 bit resolution.
- Digitally programmable corner frequency allows selecting cut-off frequencies specific to each application
- Plug-in ready-to-use, reducing engineering design and manufacturing cycle time.
- Factory tuned, no external clocks or adjustments needed
- Broad range of transfer characteristics and corner frequencies to meet a wide range of applications.

Applications

- Anti-alias filtering
- Data acquisition systems
- Communication systems and electronics
- Medical electronics equipment and research
- Aerospace, navigation and sonar applications
- Acoustic and vibration analysis and control
- Real and compressed time data analysis
- Noise elimination
- Signal reconstruction

Pin-Out & Package Data



Available 424 Low-Pass Models:

- 424L4B 4-pole Butterworth
- 424L4L 4-pole Bessel
- 424L4Y2 4-pole Cheby (0.2 dB Ripple)
- 424L4Y5 4-pole Cheby (0.5 dB Ripple)

Available 424 High-Pass Models:

- 424H4B 4-pole Butterworth
- 424H4Y2 4-pole Cheby (0.2 dB Ripple)
- 424H4Y5 4-pole Cheby (0.5 dB Ripple)

Available 428 Low-Pass Models:

- 428L4B 8-pole Butterworth
- 428L4E 8-pole, 6 zero elliptic, 1.77 (-80dB)
- 428L4EX 8-pole, 6 zero elliptic, 1.56 (-80dB)
- 428L4EY 8-pole, 6 zero elliptic, 2.00 (-100dB)
- 428L4L 8-pole Bessel
- 428L4D60 8-pole constant delay (-60 dB)
- 428L4D80 8-pole constant delay (-80 dB)
- 428L4D10 8-pole constant delay (-100 dB)

Available 428 High-Pass Models:

- 428H4B 8-pole Butterworth
- 428H4E 8-pole, 6 zero elliptic, 1.77 (-80dB)
- 428H4EX 8-pole, 6 zero elliptic, 1.56 (-80dB)
- 428H4EY 8-pole, 6 zero elliptic, 2.00 (-100dB)

3731130 0002796 236

25 Locust St. • Haverhill, Massachusetts 01830 • (800) 252-7074 • (978) 374-0761 • FAX (978) 521-1839
 e-mail: sales@freqdev.com • Web Address: <http://www.freqdev.com> • Fax on Demand: 978/521-5178



Specification
(25°C and Vs ± 15 Vdc)

Ordering Information

Analog Input Characteristics¹

Impedance 10 k Ω min.
Voltage Range ± 10 V_{peak}
Max. Safe Voltage ±Vs

Analog Output Characteristics

Impedance (Closed Loop) 1 Ω typ.
10 Ω max.
Linear Operating Range ±10V
Maximum Current² ±2 mA
Offset Voltage³ 2 mV typ.
20 mV max.
Offset Temp. Coeff. 50 μ/°C

Power Supply (±V)

Rated Voltage ±15 Vdc
Operating Range ±12 to ±18 Vdc
Maximum Safe Voltage ±18 Vdc

Quiescent Current


424, 4-Pole ±13 mA typ.
±20 mA max.
428, 8-Pole ±25 mA typ.
±40 mA max.

Temperature

Operating 0 to +70°C
Storage -25 to +85°C

Notes:

1. Input and output signal voltage referenced to supply common.
2. Output is short circuit protected to common.
DO NOT CONNECT TO ±Vs.
3. Adjustable to zero.
4. Units operate with or without offset pin connected.



Ordering Information

Filter Type

L - Low Pass
H - High Pass

Poles

4 - 4 Pole
8 - 8 Pole

424 Transfer Function

B - Butterworth
L - Bessel
Y2 - 0.2 Ripple Chebychev
Y5 - 0.5 Ripple Chebychev

428 Transfer Function

B - Butterworth
L - Bessel
D60 - constant delay (-60 dB)
D80 - constant delay (-80 dB)
D10 - constant delay (-100 dB)
E - elliptic 1.77 (-80 dB)
EX - elliptic 1.56 (-80 dB)
EY - elliptic 2.00 (-100 dB)

428 L4E-L7

Model Number

Binary Tuning Ranges

Model Number	Tuning Range (Hz)	*Minimum Step (Hz)	424 Case	428 Case
1	10-160	10	B-1	B-2
2	25-400	25	B-1	B-2
3	50-800	50	B-1	B-2
4	100-1.60k	100	B-1	B-2
5	250-4.00k	250	B-1	B-2
6	500-8.00k	500	B-1	B-2
7	1.00k-16.0k	1.00k	B-1	B-2
8	2.50k-40.0k	2.50k	B-1	B-2
9	5.00k-80.0k	5.00k	B-1	B-2
10	6.40k-102.4k	6.40k	B-1	B-2

*Contact factory for custom step frequency. Maximum step 6.40 kHz.

Log Weighted Tuning Ranges

Model Number	Log Weighted Frequency's (Hz)	424 Case	428 Case
L1	10, 30, 100, 300, 1.00k	B-1	B-2
L2	25, 75, 250, 750, 2.50k	B-1	B-2
L3	50, 300, 500, 1.50k, 5.00k	B-1	B-2
L4	100, 300, 1.00k, 3.00k, 10.0k	B-1	B-2
L5	250, 750, 2.50k, 7.50k, 25.0k	B-1	B-2
L6	500, 1.50k, 5.00k, 15.0k, 50.0k	B-1	B-2
L7	1.00k, 3.00k, 10.0k, 30.0k, 100.0k	B-1	B-2

*Contact factory for custom frequency's.

Discrete Frequency's

Customer must specify f₁, f₂, f₃, f₄, f₅. Maximum span f₁ ⇒ f₅ 1,000:1.
Contact factory for custom frequency's

88063

We hope the information given here will be helpful. The information is based on data and our best knowledge, and we consider the information to be true and accurate. Please read all statements, recommendations or suggestions herein in conjunction with our conditions of sale which apply to all goods supplied by us. We assume no responsibility for the use of these statements, recommendations or suggestions, nor do we intend them as a recommendation for any use which would infringe any patent or copyright.

PR-424/428-00

25 Locust St. • Haverhill, Massachusetts 01830 • (800) 252-7074 • (978) 374-0761 • FAX (978) 521-1839
e-mail: sales@freqdev.com • Web Address: http://www.freqdev.com • Fax on Demand: 978/521-5178

