


Phototransistor Output, GaAs Input										
Part Number	CTR @ 10 mA I <sub>F</sub> (%)		BV <sub>CEO</sub> (V)	BV <sub>CBO</sub> (V)	V <sub>CE (sat)</sub> (V)	t <sub>ON</sub> /t <sub>OFF</sub> (μs)	V <sub>ISO</sub> AC[RMS]	Pkg dwg	Agency Approvals (see pg 23)	
	min	max	min	min	max	max				
4N25	20	—	30	70	0.5	—	5.3 kV	C	A, B, D, F, N, S, U	
4N25.300	20	—	30	70	0.5	—	5.3 kV	C	A, B, D, F, N, S, U, V	
4N26	20	—	30	70	0.5	—	5.3 kV	C	A, B, D, F, N, S, U	
4N26.300	20	—	30	70	0.5	—	5.3 kV	C	A, B, D, F, N, S, U, V	
4N27	10	—	30	70	0.5	—	5.3 kV	C	A, B, D, F, N, S, U	
4N27.300	10	—	30	70	0.5	—	5.3 kV	C	A, B, D, F, N, S, U, V	
4N28	10	—	30	70	0.5	—	5.3 kV	C	A, B, D, F, N, S, U	
4N28.300	10	—	30	70	0.5	—	5.3 kV	C	A, B, D, F, N, S, U, V	
4N35	100	—	30	70	0.3	10/10	5.3 kV	C	A, B, D, F, N, S, U	
4N35.300	100	—	30	70	0.3	10/10	5.3 kV	C	A, B, D, F, N, S, U, V	
4N36	100	—	30	70	0.3	10/10	5.3 kV	C	A, B, D, F, N, S, U	
4N36.300	100	—	30	70	0.3	10/10	5.3 kV	C	A, B, D, F, N, S, U, V	
4N37	100	—	30	70	0.3	10/10	5.3 kV	C	A, B, D, F, N, S, U	
4N37.300	100	—	30	70	0.3	10/10	5.3 kV	C	A, B, D, F, N, S, U, V	
CNW11AV-1	100	300	70	70	0.4	15/15	4.0 kV	A	A, B, D, F, N, S, U	
CNW11AV-1.300	100	300	70	70	0.4	15/15	4.0 kV	A	A, B, D, F, N, S, U, V	
CNW11AV-2	50	—	70	70	0.4	15/15	4.0 kV	A	A, B, D, F, N, S, U	
CNW11AV-2.300	50	—	70	70	0.4	15/15	4.0 kV	A	A, B, D, F, N, S, U, V	
CNW11AV-3	20	—	70	70	0.4	15/15	4.0 kV	A	A, B, D, F, N, S, U	
CNW11AV-3.300	20	—	70	70	0.4	15/15	4.0 kV	A	A, B, D, F, N, S, U, V	
CNW83	40	—	50	70	0.4	—	5.9 kV	A	A, B, D, F, N, S, U	
CNW83.300	40	—	50	70	0.4	—	5.9 kV	A	A, B, D, F, N, S, U, V	
CNW85	63	320	80	120	0.4	—	5.9 kV	A	A, B, D, F, N, S, U	
CNW85.300	63	320	80	120	0.4	—	5.9 kV	A	A, B, D, F, N, S, U, V	
CNX35U	40	160	30	70	0.4	20/20	5.3 kV	C	A, B, D, F, N, S, U	
CNX35U.300	40	160	30	70	0.4	20/20	5.3 kV	C	A, B, D, F, N, S, U, V	
CNX36U	80	200	30	70	0.4	20/20	5.3 kV	C	A, B, D, F, N, S, U	
CNX36U.300	80	200	30	70	0.4	20/20	5.3 kV	C	A, B, D, F, N, S, U, V	
CNX38U	70	210	80	120	0.4	20/20	5.3 kV	C	A, B, D, F, N, S, U	
CNX38U.300	70	210	80	120	0.4	20/20	5.3 kV	C	A, B, D, F, N, S, U, V	
CNX39U	60	100	30	70	0.4	20/20	5.3 kV	C	A, B, D, F, N, S, U	
CNX39U.300	60	100	30	70	0.4	20/20	5.3 kV	C	A, B, D, F, N, S, U, V	
CNX83A	40	—	50	70	0.4	—	5.3 kV	C	A, B, D, F, N, S, U	
CNX83A.300	40	—	50	70	0.4	—	5.3 kV	C	A, B, D, F, N, S, U, V	
CNY17-1	40	80	70	70	0.4	10/10	5.3 kV	C	A, B, D, F, N, S, U	


**Notes**

A complete list of agencies appears on page 23.  
 Optocoupler Package outlines appear on pages 24, 25, and 26.