

DATA SHEET

An ON Semiconductor Company

# **CPH3910**-

N-Channel Junctin Silicon FET

# **High-Frequency Low-Noise Amplifier Applications**

# **Applications**

- · For AM tuner RF amplification
- · Low noise amplifier

### Features

- V<sub>GDS</sub>: -25V max.
- | yfs |: 40mS typ.
- Ciss: 6.0pF typ.
- NF: 2.1dB typ.


## **Specifications**

#### Absolute Maximum Ratings at Ta=25°C

Parameter	Symbol	Conditions	Ratings	Unit
Drain-to-Source Voltage	VDSX		25	V
Gate-to-Drain Voltage	VGDS		-25	V
Gate Current	IG		10	mA
Drain Current	ID		50	mA
Allowable Power Dissipation	PD		400	mW
Junction Temperature	Tj		150	°C
Storage Temperature	Tstg		-55 to +150	°C

#### Package Dimensions


unit : mm (typ) 7015A-007



#### **Product & Package Information** Package

- : CPH3
- JEITA, JEDEC : SC-59, TO-236, SOT-23
- Minimum Packing Quantity : 3,000 pcs./reel

#### Packing Type: TL






#### **Electrical Connection**




#### SANYO Semiconductor Co., Ltd. http://semicon.sanyo.com/en/network

#### Electrical Characteristics at Ta=25°C

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	Unit
Gate-to-Drain Breakdown Voltage	V(BR)GDS	IG=-10μΑ, VDS=0V	-25			V
Gate Cutoff Current	IGSS	V <sub>GS</sub> =-10V, V <sub>DS</sub> =0V			-1.0	nA
Cutoff Voltage	V <sub>GS</sub> (off)	V <sub>DS</sub> =5V, I <sub>D</sub> =100μA	-0.6	-1.2	-1.8	V
Drain Current	IDSS	V <sub>DS</sub> =5V, V <sub>GS</sub> =0V	20		40	mA
Forward Transfer Admittance	yfs	V <sub>DS</sub> =5V, V <sub>GS</sub> =0V, f=1kHz	30	40		mS
Input Capacitance	Ciss	V <sub>DS</sub> =5V, V <sub>GS</sub> =0V, f=1MHz		6.0		рF
Reverse Transfer Capacitance	Crss	V <sub>DS</sub> =5V, V <sub>GS</sub> =0V, f=1MHz		2.3		pF
Noise Figure	NF	V <sub>DS</sub> =5V, V <sub>GS</sub> =0V, f=100MHz		2.1	2.8	dB






2

100 IT16692

5

Drain Current, IDSS - mA



- Any and all SANYO Semiconductor Co.,Ltd. products described or contained herein are, with regard to "standard application", intended for the use as general electronics equipment. The products mentioned herein shall not be intended for use for any "special application" (medical equipment whose purpose is to sustain life, aerospace instrument, nuclear control device, burning appliances, transportation machine, traffic signal system, safety equipment etc.) that shall require extremely high level of reliability and can directly threaten human lives in case of failure or malfunction of the product or may cause harm to human bodies, nor shall they grant any guarantee thereof. If you should intend to use our products for new introduction or other application different from current conditions on the usage of automotive device, communication device, office equipment, industrial equipment etc.. , please consult with us about usage condition (temperature, operation time etc.) prior to the intended use. If there is no consultation or inquiry before the intended use, our customer shall be solely responsible for the use.
- Specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Semiconductor Co.,Ltd. assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all SANYO Semiconductor Co.,Ltd. products described or contained herein.
- SANYO Semiconductor Co.,Ltd. strives to supply high-quality high-reliability products, however, any and all semiconductor products fail or malfunction with some probability. It is possible that these probabilistic failures or malfunction could give rise to accidents or events that could endanger human lives, trouble that could give rise to smoke or fire, or accidents that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO Semiconductor Co.,Ltd. products described or contained herein are controlled under any of applicable local export control laws and regulations, such products may require the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written consent of SANYO Semiconductor Co.,Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO Semiconductor Co.,Ltd. product that you intend to use.
- Upon using the technical information or products described herein, neither warranty nor license shall be granted with regard to intellectual property rights or any other rights of SANYO Semiconductor Co.,Ltd. or any third party. SANYO Semiconductor Co.,Ltd. shall not be liable for any claim or suits with regard to a third party's intellectual property rights which has resulted from the use of the technical information and products mentioned above.

This catalog provides information as of February, 2012. Specifications and information herein are subject to change without notice.