

KR Electronics

General Description


KR 2618-3-SMA is a 100 MHz bandpass filter. Other center frequencies and bandwidths available. Please consult the factory.

Features


- 100 MHz Center Frequency
- SMA Connectors
- 50 Ω Source and Load

Typical Performance

Passband Amplitude & Group Delay (1 dB/div & 10 nsec/div)



Overall Response (10 dB/div)



KR Electronics, Inc.
91 Avenel Street
Avenel, NJ 07001


Web www.krfilters.com
Email sales@krfilters.com
Phone (732) 636-1900
Fax (732) 636-1982

KR 2618-3-SMA Bandpass

Specifications

Parameter	Specification
Filter type	Bandpass
Center Frequency	100 MHz
Insertion Loss	< 6 dB (4 dB typical)
1 dB Bandwidth	> ± 2 MHz min
Source and Load	50 Ω

Physical Dimensions



Notes:

1. Dimensions in inches
2. Also available in a surface mount package