



## DATA SHEET

# BIPOLAR ANALOG INTEGRATED CIRCUIT $\mu$ PC79Mxx Series

## THREE TERMINAL NEGATIVE VOLTAGE REGULATOR

### <R> DESCRIPTION

The  $\mu$ PC79Mxx Series are three-terminal negative output voltage stabilization power supply circuit of fixed output voltage. It regulates non-stabilized DC input voltage to output stabilized fixed voltage.

The six types of voltage value are -5 V, -8 V, -12 V, -15 V, -18 V and -24 V, and they can be respectively used as power supply circuit with maximum current capacity 500 mA.

### FEATURES

- Output current : 500 mA
- On-chip some protection circuits
  - (over current protection, SOA protection and thermal shut down)
- Low noise

### <R> ORDERING INFORMATION

Part Number	Package	Output Voltage	Marking	Package Type
$\mu$ PC79M05HF	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-5 V	79M05	Packed in envelope
$\mu$ PC79M05HF-AZ <sup>Note</sup>	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-5 V	79M05	Packed in envelope
$\mu$ PC79M08HF	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-8 V	79M08	Packed in envelope
$\mu$ PC79M08HF-AZ <sup>Note</sup>	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-8 V	79M08	Packed in envelope
$\mu$ PC79M12HF	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-12 V	79M12	Packed in envelope
$\mu$ PC79M12HF-AZ <sup>Note</sup>	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-12 V	79M12	Packed in envelope
$\mu$ PC79M15HF	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-15 V	79M15	Packed in envelope
$\mu$ PC79M15HF-AZ <sup>Note</sup>	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-15 V	79M15	Packed in envelope
$\mu$ PC79M18HF	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-18 V	79M18	Packed in envelope
$\mu$ PC79M18HF-AZ <sup>Note</sup>	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-18 V	79M18	Packed in envelope
$\mu$ PC79M24HF	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-24 V	79M24	Packed in envelope
$\mu$ PC79M24HF-AZ <sup>Note</sup>	3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)	-24 V	79M24	Packed in envelope



**Note** Pb-free (This product does not contain Pb in external electrode).

**Remark** Output voltage -5 V product is written in the text as  $\mu$ PC79M05.  
It applies to other output voltage products as same.

The information in this document is subject to change without notice. Before using this document, please confirm that this is the latest version.  
Not all products and/or types are available in every country. Please check with an NEC Electronics sales representative for availability and additional information.

**PIN CONFIGURATION (Marking Side)**

3-PIN PLASTIC SIP (MP-45G) (Isolated TO-220)

**EQUIVALENT CIRCUIT**

ABSOLUTE MAXIMUM RATINGS ( $T_A = 25^\circ\text{C}$ , unless otherwise specified)


Parameter	Symbol	Rating	Unit
Input Voltage	$V_{IN}$	-35/-40 <sup>Note1</sup>	V
Internal Power Dissipation	$P_T$	15 <sup>Note2</sup>	W
Operating Ambient Temperature	$T_A$	-20 to +85	$^\circ\text{C}$
Operating Junction Temperature	$T_J$	-20 to +150	$^\circ\text{C}$
Storage Temperature	$T_{STG}$	-55 to +150	$^\circ\text{C}$
Thermal Resistance (junction to case)	$R_{th(J-C)}$	7	$^\circ\text{C}/\text{W}$
Thermal Resistance (junction to ambient)	$R_{th(J-A)}$	65	$^\circ\text{C}/\text{W}$

**Notes 1.**  $\mu$ PC79M05, 08, 12, 15, 18 : -35 V,  $\mu$ PC79M24 : -40 V

2. Internally limited. When operating junction temperature rise above 150°C, the internal protection circuit shutdown output voltage.

<R> **Caution** Product quality may suffer if the absolute maximum rating is exceeded even momentarily for any parameter. That is, the absolute maximum ratings are rated values at which the product is on the verge of suffering physical damage, and therefore the product must be used under conditions that ensure that the absolute maximum ratings are not exceeded.

## &lt;R&gt; TYPICAL CONNECTION



$C_{IN}$  : Required if regulator is located an appreciable distance from power supply filter. (More than 2  $\mu\text{F}$ )

$C_{OUT}$ : Connect it within 2 cm from OUTPUT pin and GND pin (More than 1  $\mu\text{F}$ ).

D<sub>1</sub> : Needed for  $V_{IN} > V_o$ .

D<sub>2</sub> : Needed for  $V_o > GND$ .

## RECOMMENDED OPERATING CONDITIONS

Parameter	Symbol	Type Number	MIN.	TYP.	MAX.	Unit
Input Voltage	$V_{IN}$	$\mu$ PC79M05	-7	-10	-25	V
		$\mu$ PC79M08	-10.5	-14	-25	V
		$\mu$ PC79M12	-14.5	-19	-30	V
		$\mu$ PC79M15	-17.5	-23	-30	V
		$\mu$ PC79M18	-21	-27	-33	V
		$\mu$ PC79M24	-27	-33	-38	V
Output Current	$I_o$	All	5		350	mA
Operating Ambient Temperature	$T_A$	All	-20		+85	$^\circ\text{C}$
Operating Junction Temperature	$T_J$	All	-20		+125	$^\circ\text{C}$

## ELECTRICAL CHARACTERISTICS

 $\mu$ PC79M05 ( $V_{IN} = -10$  V,  $I_o = 350$  mA,  $0^\circ C \leq T_J \leq +125^\circ C$ ,  $C_{IN} = 2.2 \mu F$ ,  $C_{OUT} = 1 \mu F$ , unless otherwise specified)

Parameter	Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Output Voltage	$V_o$	$T_J = 25^\circ C$	-4.8	-5.0	-5.2	V
		$-7 V \leq V_{IN} \leq -25 V$ , $5 mA \leq I_o \leq 350 mA$	-4.75		-5.25	V
Line Regulation	$REG_{IN}$	$T_J = 25^\circ C$ , $-7 V \leq V_{IN} \leq -25 V$		18	50	mV
		$T_J = 25^\circ C$ , $-8 V \leq V_{IN} \leq -18 V$		10	30	mV
Load Regulation	$REG_L$	$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 500 mA$		15	100	mV
		$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 350 mA$		10		mV
Quiescent Current	$I_{BIAS}$	$T_J = 25^\circ C$		4.3	6.0	mA
Quiescent Current Change	$\Delta I_{BIAS}$	$-8 V \leq V_{IN} \leq -25 V$			0.5	mA
		$5 mA \leq I_o \leq 350 mA$			0.4	mA
Output Noise Voltage	$V_n$	$T_J = 25^\circ C$ , $10 Hz \leq f \leq 100 kHz$		45	200	$\mu V_{r.m.s.}$
Ripple Rejection	$R \cdot R$	$T_J = 25^\circ C$ , $-8 V \leq V_{IN} \leq -18 V$ , $f = 120 Hz$ , $I_o = 100 mA$	50	72		dB
Dropout Voltage	$V_{DIF}$	$T_J = 25^\circ C$		1.1		V
Short Circuit Current	$I_{Oshort}$	$T_J = 25^\circ C$ , $V_{IN} = -25 V$		500		mA
Peak Output Current	$I_{Opeak}$	$T_J = 25^\circ C$	620	880	1020	mA
Temperature Coefficient of Output Voltage	$\Delta V_o / \Delta T$	$I_o = 5 mA$		0.2		$mV/^\circ C$

 $\mu$ PC79M08 ( $V_{IN} = -14$  V,  $I_o = 350$  mA,  $0^\circ C \leq T_J \leq +125^\circ C$ ,  $C_{IN} = 2.2 \mu F$ ,  $C_{OUT} = 1 \mu F$ , unless otherwise specified)

Parameter	Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Output Voltage	$V_o$	$T_J = 25^\circ C$	-7.7	-8.0	-8.3	V
		$-10.5 V \leq V_{IN} \leq -25 V$ , $5 mA \leq I_o \leq 350 mA$	-7.6		-8.4	V
Line Regulation	$REG_{IN}$	$T_J = 25^\circ C$ , $-10.5 V \leq V_{IN} \leq -25 V$		20	80	mV
		$T_J = 25^\circ C$ , $-11 V \leq V_{IN} \leq -21 V$		15	50	mV
Load Regulation	$REG_L$	$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 500 mA$		20	160	mV
		$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 350 mA$		15		mV
Quiescent Current	$I_{BIAS}$	$T_J = 25^\circ C$		4.3	6.0	mA
Quiescent Current Change	$\Delta I_{BIAS}$	$-10.5 V \leq V_{IN} \leq -25 V$			0.5	mA
		$5 mA \leq I_o \leq 350 mA$			0.4	mA
Output Noise Voltage	$V_n$	$T_J = 25^\circ C$ , $10 Hz \leq f \leq 100 kHz$		65	220	$\mu V_{r.m.s.}$
Ripple Rejection	$R \cdot R$	$T_J = 25^\circ C$ , $-11.5 V \leq V_{IN} \leq -21.5 V$ , $f = 120 Hz$ , $I_o = 100 mA$	50	66		dB
Dropout Voltage	$V_{DIF}$	$T_J = 25^\circ C$		1.1		V
Short Circuit Current	$I_{Oshort}$	$T_J = 25^\circ C$ , $V_{IN} = -25 V$		500		mA
Peak Output Current	$I_{Opeak}$	$T_J = 25^\circ C$	620	880	1020	mA
Temperature Coefficient of Output Voltage	$\Delta V_o / \Delta T$	$I_o = 5 mA$		0.3		$mV/^\circ C$

$\mu$ PC79M12 ( $V_{IN} = -19$  V,  $I_o = 350$  mA,  $0^\circ C \leq T_J \leq +125^\circ C$ ,  $C_{IN} = 2.2 \mu F$ ,  $C_{OUT} = 1 \mu F$ , unless otherwise specified)

Parameter	Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Output Voltage	$V_o$	$T_J = 25^\circ C$	-11.5	-12.0	-12.5	V
		$-14.5 V \leq V_{IN} \leq -30 V$ , $5 mA \leq I_o \leq 350 mA$	-11.4		-12.6	V
Line Regulation	$REG_{IN}$	$T_J = 25^\circ C$ , $-14.5 V \leq V_{IN} \leq -30 V$		25	80	mV
		$T_J = 25^\circ C$ , $-15 V \leq V_{IN} \leq -25 V$		20	50	mV
Load Regulation	$REG_L$	$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 500 mA$		35	240	mV
		$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 350 mA$		25		mV
Quiescent Current	$I_{BIAS}$	$T_J = 25^\circ C$		4.4	6.0	mA
Quiescent Current Change	$\Delta I_{BIAS}$	$-14.5 V \leq V_{IN} \leq -30 V$			0.5	mA
		$5 mA \leq I_o \leq 350 mA$			0.4	mA
Output Noise Voltage	$V_n$	$T_J = 25^\circ C$ , $10 Hz \leq f \leq 100 kHz$		125	280	$\mu V_{r.m.s.}$
Ripple Rejection	$R \cdot R$	$T_J = 25^\circ C$ , $-15 V \leq V_{IN} \leq -25 V$ , $f = 120 Hz$ , $I_o = 100 mA$	50	64		dB
Dropout Voltage	$V_{DIF}$	$T_J = 25^\circ C$		1.1		V
Short Circuit Current	$I_{Oshort}$	$T_J = 25^\circ C$ , $V_{IN} = -30 V$		400		mA
Peak Output Current	$I_{Opeak}$	$T_J = 25^\circ C$	620	880	1020	mA
Temperature Coefficient of Output Voltage	$\Delta V_o / \Delta T$	$I_o = 5 mA$		0.4		$mV/^\circ C$

 $\mu$ PC79M15 ( $V_{IN} = -23$  V,  $I_o = 350$  mA,  $0^\circ C \leq T_J \leq +125^\circ C$ ,  $C_{IN} = 2.2 \mu F$ ,  $C_{OUT} = 1 \mu F$ , unless otherwise specified)







Parameter	Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Output Voltage	$V_o$	$T_J = 25^\circ C$	-14.4	-15.0	-15.6	V
		$-17.5 V \leq V_{IN} \leq -30 V$ , $5 mA \leq I_o \leq 350 mA$	-14.25		-15.75	V
Line Regulation	$REG_{IN}$	$T_J = 25^\circ C$ , $-17.5 V \leq V_{IN} \leq -30 V$		30	80	mV
		$T_J = 25^\circ C$ , $-18 V \leq V_{IN} \leq -28 V$		25	50	mV
Load Regulation	$REG_L$	$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 500 mA$		50	240	mV
		$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 350 mA$		35		mV
Quiescent Current	$I_{BIAS}$	$T_J = 25^\circ C$		4.4	6.0	mA
Quiescent Current Change	$\Delta I_{BIAS}$	$-17.5 V \leq V_{IN} \leq -30 V$			0.5	mA
		$5 mA \leq I_o \leq 350 mA$			0.4	mA
Output Noise Voltage	$V_n$	$T_J = 25^\circ C$ , $10 Hz \leq f \leq 100 kHz$		150	360	$\mu V_{r.m.s.}$
Ripple Rejection	$R \cdot R$	$T_J = 25^\circ C$ , $-18.5 V \leq V_{IN} \leq -28.5 V$ , $f = 120 Hz$ , $I_o = 100 mA$	50	62		dB
Dropout Voltage	$V_{DIF}$	$T_J = 25^\circ C$		1.1		V
Short Circuit Current	$I_{Oshort}$	$T_J = 25^\circ C$ , $V_{IN} = -30 V$		400		mA
Peak Output Current	$I_{Opeak}$	$T_J = 25^\circ C$	620	880	1020	mA
Temperature Coefficient of Output Voltage	$\Delta V_o / \Delta T$	$I_o = 5 mA$		0.6		$mV/^\circ C$





$\mu$ PC79M18 ( $V_{IN} = -27$  V,  $I_o = 350$  mA,  $0^\circ C \leq T_J \leq +125^\circ C$ ,  $C_{IN} = 2.2 \mu F$ ,  $C_{OUT} = 1 \mu F$ , unless otherwise specified)

Parameter	Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Output Voltage	$V_o$	$T_J = 25^\circ C$	-17.3	-18.0	-18.7	V
		$-21 V \leq V_{IN} \leq -33 V$ , $5 mA \leq I_o \leq 350 mA$	-17.1		-18.9	V
Line Regulation	$REG_{IN}$	$T_J = 25^\circ C$ , $-21 V \leq V_{IN} \leq -33 V$		30	80	mV
		$T_J = 25^\circ C$ , $-24 V \leq V_{IN} \leq -30 V$		25	50	mV
Load Regulation	$REG_L$	$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 500 mA$		60	300	mV
		$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 350 mA$		45		mV
Quiescent Current	$I_{BIAS}$	$T_J = 25^\circ C$		4.4	6.0	mA
Quiescent Current Change	$\Delta I_{BIAS}$	$-21 V \leq V_{IN} \leq -33 V$			0.5	mA
		$5 mA \leq I_o \leq 350 mA$			0.4	mA
Output Noise Voltage	$V_n$	$T_J = 25^\circ C$ , $10 Hz \leq f \leq 100 kHz$		200	440	$\mu V_{r.m.s.}$
Ripple Rejection	$R \cdot R$	$T_J = 25^\circ C$ , $-22 V \leq V_{IN} \leq -32 V$ , $f = 120 Hz$ , $I_o = 100 mA$	50	60		dB
Dropout Voltage	$V_{DIF}$	$T_J = 25^\circ C$		1.1		V
Short Circuit Current	$I_{Oshort}$	$T_J = 25^\circ C$ , $V_{IN} = -33 V$		350		mA
Peak Output Current	$I_{Opeak}$	$T_J = 25^\circ C$	620	880	1020	mA
Temperature Coefficient of Output Voltage	$\Delta V_o / \Delta T$	$I_o = 5 mA$		0.8		$mV/^\circ C$

 $\mu$ PC79M24 ( $V_{IN} = -33$  V,  $I_o = 350$  mA,  $0^\circ C \leq T_J \leq +125^\circ C$ ,  $C_{IN} = 2.2 \mu F$ ,  $C_{OUT} = 1 \mu F$ , unless otherwise specified)


Parameter	Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Output Voltage	$V_o$	$T_J = 25^\circ C$	-23.0	-24.0	-25.0	V
		$-27 V \leq V_{IN} \leq -38 V$ , $5 mA \leq I_o \leq 350 mA$	-22.8		-25.2	V
Line Regulation	$REG_{IN}$	$T_J = 25^\circ C$ , $-27 V \leq V_{IN} \leq -38 V$		30	80	mV
		$T_J = 25^\circ C$ , $-30 V \leq V_{IN} \leq -36 V$		25	50	mV
Load Regulation	$REG_L$	$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 500 mA$		80	360	mV
		$T_J = 25^\circ C$ , $5 mA \leq I_o \leq 350 mA$		50		mV
Quiescent Current	$I_{BIAS}$	$T_J = 25^\circ C$		4.5	6.0	mA
Quiescent Current Change	$\Delta I_{BIAS}$	$-27 V \leq V_{IN} \leq -38 V$			0.5	mA
		$5 mA \leq I_o \leq 350 mA$			0.4	mA
Output Noise Voltage	$V_n$	$T_J = 25^\circ C$ , $10 Hz \leq f \leq 100 kHz$		250	600	$\mu V_{r.m.s.}$
Ripple Rejection	$R \cdot R$	$T_J = 25^\circ C$ , $-28 V \leq V_{IN} \leq -38 V$ , $f = 120 Hz$ , $I_o = 100 mA$	50	57		dB
Dropout Voltage	$V_{DIF}$	$T_J = 25^\circ C$		1.1		V
Short Circuit Current	$I_{Oshort}$	$T_J = 25^\circ C$ , $V_{IN} = -38 V$		200		mA
Peak Output Current	$I_{Opeak}$	$T_J = 25^\circ C$	620	880	1020	mA
Temperature Coefficient of Output Voltage	$\Delta V_o / \Delta T$	$I_o = 5 mA$		1.0		$mV/^\circ C$

TYPICAL CHARACTERISTICS ( $T_J = 25^\circ\text{C}$ , unless otherwise specified)



&lt;R&gt; PACKAGE DRAWING (Unit: mm)

## 3PIN PLASTIC SIP (MP-45G)



## NOTE

Each lead centerline is located within 0.25 mm of its true position (T.P.) at maximum material condition.

ITEM	MILLIMETERS
A	10.0±0.2
B	7.0±0.2
C	1.50±0.2
D	17.0±0.3
E	$\phi$ 3.3±0.2
F	0.75±0.10
G	0.25
H	2.54 (T.P.)
I	5.0±0.3
J	2.46±0.2
K	5.0±0.2
L	8.5±0.2
M	8.5±0.2
N	4.5±0.2
P	2.8±0.2
U	2.4±0.5
V	0.65±0.10
Y	8.9±0.7
Z	1.30±0.2

P3HF-254B-4

## &lt;R&gt; RECOMMENDED SOLDERING CONDITIONS

The  $\mu$ PC79Mxx Series should be soldered and mounted under the following recommended conditions.

For soldering methods and conditions other than those recommended below, contact an NEC Electronics sales representative.

For technical information, see the following website.

Semiconductor Device Mount Manual (<http://www.necel.com/pkg/en/mount/index.html>)

**Through-hole devices**

$\mu$ PC79M05HF, 79M08HF, 79M12HF, 79M15HF, 79M18HF, 79M24HF,

$\mu$ PC79M05HF-AZ, 79M08HF-AZ, 79M12HF-AZ, 79M15HF-AZ, 79M18HF-AZ, 79M24HF-AZ : 3-PIN PLASTIC SIP (MP-45G)

(Isolated TO-220)

Process	Conditions	Symbol
Wave soldering (only to leads)	Solder temperature: 260°C or below, Flow time: 10 seconds or less, Maximum number of flow processes: 1 time.	WS60-00-1
Partial heating method	Pin temperature: 350°C or below, Heat time: 3 seconds or less (Per each pin).	P350

**Caution For through-hole device, the wave soldering process must be applied only to leads, and make sure that the package body does not get jet soldered.**

## &lt;R&gt; REFERENCE DOCUMENTS

Document Name	Document No.
Usage of Three-Terminal Regulators User's Manual	G12702E
Semiconductor Device Mount Manual	<a href="http://www.necel.com/pkg/en/mount/index.html">http://www.necel.com/pkg/en/mount/index.html</a>
Review of Quality and Reliability Handbook Information	C12769E

- The information in this document is current as of January, 2007. The information is subject to change without notice. For actual design-in, refer to the latest publications of NEC Electronics data sheets or data books, etc., for the most up-to-date specifications of NEC Electronics products. Not all products and/or types are available in every country. Please check with an NEC Electronics sales representative for availability and additional information.
- No part of this document may be copied or reproduced in any form or by any means without the prior written consent of NEC Electronics. NEC Electronics assumes no responsibility for any errors that may appear in this document.
- NEC Electronics does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from the use of NEC Electronics products listed in this document or any other liability arising from the use of such products. No license, express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC Electronics or others.
- Descriptions of circuits, software and other related information in this document are provided for illustrative purposes in semiconductor product operation and application examples. The incorporation of these circuits, software and information in the design of a customer's equipment shall be done under the full responsibility of the customer. NEC Electronics assumes no responsibility for any losses incurred by customers or third parties arising from the use of these circuits, software and information.
- While NEC Electronics endeavors to enhance the quality, reliability and safety of NEC Electronics products, customers agree and acknowledge that the possibility of defects thereof cannot be eliminated entirely. To minimize risks of damage to property or injury (including death) to persons arising from defects in NEC Electronics products, customers must incorporate sufficient safety measures in their design, such as redundancy, fire-containment and anti-failure features.
- NEC Electronics products are classified into the following three quality grades: "Standard", "Special" and "Specific".

The "Specific" quality grade applies only to NEC Electronics products developed based on a customer-designated "quality assurance program" for a specific application. The recommended applications of an NEC Electronics product depend on its quality grade, as indicated below. Customers must check the quality grade of each NEC Electronics product before using it in a particular application.

"Standard": Computers, office equipment, communications equipment, test and measurement equipment, audio and visual equipment, home electronic appliances, machine tools, personal electronic equipment and industrial robots.

"Special": Transportation equipment (automobiles, trains, ships, etc.), traffic control systems, anti-disaster systems, anti-crime systems, safety equipment and medical equipment (not specifically designed for life support).

"Specific": Aircraft, aerospace equipment, submersible repeaters, nuclear reactor control systems, life support systems and medical equipment for life support, etc.

The quality grade of NEC Electronics products is "Standard" unless otherwise expressly specified in NEC Electronics data sheets or data books, etc. If customers wish to use NEC Electronics products in applications not intended by NEC Electronics, they must contact an NEC Electronics sales representative in advance to determine NEC Electronics' willingness to support a given application.

(Note)

- (1) "NEC Electronics" as used in this statement means NEC Electronics Corporation and also includes its majority-owned subsidiaries.
- (2) "NEC Electronics products" means any product developed or manufactured by or for NEC Electronics (as defined above).