MAZQxxx Series

Silicon planar type

For constant voltage, constant current, waveform clipper and surge absorption circuit

■ Features

- Optimum for high-density mounting
- Low noise type

■ Absolute Maximum Ratings $T_a = 25$ °C

Parameter	Symbol	Rating	Unit
Repetitive peak forward current	I_{FRM}	200	mA
Total power dissipation *	P _T	120	mW
Junction temperature	T _j	150	°C
Storage temperature	T _{stg}	-55 to +150	°C

Note) *: $P_T = 120 \text{ mW}$ achieved with a printed circuit board.

■ Package

- Code
 - USSMini2-F1
- Pin Name
 - 1: Anode
 - 2: Cathode

■ Marking Symbol

Refer to the list of the electrical characteristics within part numbers

■ Electrical Characteristics $T_a = 25$ °C±3°C

Parameter	Symbol	Conditions	Min	Тур	Max	Unit
Forward current	$V_{\rm F}$	$I_F = 10 \text{ mA}$	10es	0.9	1.0	V
Zener voltage *	Vz	I _Z Specified value —	Refer to the list of the		V	
Zene operating resistance	R_Z	I _Z Specified value	electrical characteristics within part numbers		Ω	
Reverse current	I_R	V _R Specified value			μΑ	

- Note) 1. Measuring methods are based on JAPANESE INDUSTRIAL STANDARD JIS C 7031 measuring methods for diodes.
 - 2. Absolute frequency of input and output is 5 MHz.
 - 3. The temperature must be controlled 25°C for V_Z mesurement. V_Z value measured at other temperature must be adjusted to V_Z (25°C)
 - 4. *: V_Z guaranted 20 ms after current flow.


■ Electrical Characteristics within Part Numbers $T_a = 25$ °C±3°C


Part number	Zener voltage V _Z (V)			Zener operating resistance $R_Z(\Omega)$		Reverse current I _R (μA)		Marking symbol	
	Min	Тур	Max	I _Z (mA)	Max	I _Z (mA)	Max	V _R (V)	
MAZQ062	5.8	6.2	6.6	5	30	5	0.2	4.0	Е
MAZQ068	6.4	6.8	7.2	5	20	5	0.1	4.0	F
MAZQ100	9.40	10.00	10.60	5	30	5	0.05	7	L
MAZQ200	18.80	20.00	21.20	5	80	5	0.05	15.0	V
MAZQ300	28.00	30.00	32.00	2	160	2	0.05	23.0	Y


MAZQxxx Series


Panasonic


Characteristics charts of MAZQ062, MAZQ068















Characteristics charts of MAZQ100










2 SKE00030CED








Characteristics charts of MAZQ200















SKE00030CED 3

Characteristics charts of MAZQ300










USSMini2-F1

Unit: mm



Request for your special attention and precautions in using the technical information and semiconductors described in this book

- (1) If any of the products or technical information described in this book is to be exported or provided to non-residents, the laws and regulations of the exporting country, especially, those with regard to security export control, must be observed.
- (2) The technical information described in this book is intended only to show the main characteristics and application circuit examples of the products. No license is granted in and to any intellectual property right or other right owned by Panasonic Corporation or any other company. Therefore, no responsibility is assumed by our company as to the infringement upon any such right owned by any other company which may arise as a result of the use of technical information described in this book.
- (3) The products described in this book are intended to be used for standard applications or general electronic equipment (such as office equipment, communications equipment, measuring instruments and household appliances).
 - Consult our sales staff in advance for information on the following applications:
 - Special applications (such as for airplanes, aerospace, automobiles, traffic control equipment, combustion equipment, life support systems and safety devices) in which exceptional quality and reliability are required, or if the failure or malfunction of the products may directly jeopardize life or harm the human body.
 - · Any applications other than the standard applications intended.
- (4) The products and product specifications described in this book are subject to change without notice for modification and/or improvement. At the final stage of your design, purchasing, or use of the products, therefore, ask for the most up-to-date Product Standards in advance to make sure that the latest specifications satisfy your requirements.
- (5) When designing your equipment, comply with the range of absolute maximum rating and the guaranteed operating conditions (operating power supply voltage and operating environment etc.). Especially, please be careful not to exceed the range of absolute maximum rating on the transient state, such as power-on, power-off and mode-switching. Otherwise, we will not be liable for any defect which may arise later in your equipment.
- Even when the products are used within the guaranteed values, take into the consideration of incidence of break down and failure mode, possible to occur to semiconductor products. Measures on the systems such as redundant design, arresting the spread of fire or preventing glitch are recommended in order to prevent physical injury, fire, social damages, for example, by using the products.
- (6) Comply with the instructions for use in order to prevent breakdown and characteristics change due to external factors (ESD, EOS, thermal stress and mechanical stress) at the time of handling, mounting or at customer's process. When using products for which damp-proof packing is required, satisfy the conditions, such as shelf life and the elapsed time since first opening the packages.
- (7) This book may be not reprinted or reproduced whether wholly or partially, without the prior written permission of our company.

20080805